



4 Channel FM / LoRa RF Transmitter

Features

- 4 x No-Volt Switch Inputs
- Radio Transmitter FSK/FHSS LoRa 1-7
- LoRa Mode:
 - Up to 5Km range line of sight
 - Up to 1Km range in buildings
- LED Indication: TX, ACKNOWLEDGEMENT
- Waterproof IP68 Enclosure
- Compact Size 92 x 92 x 45mm
- Ultra low power Standby mode
- Power 2 x AAA Battery (supplied) or
- 5 - 15V External Supply
- Battery Life > 1 Million Transmissions
- Screw Terminal Connections
- Operates with RF Solutions Receivers
- Optional external antenna via UFL connector



Intended Applications

- Industrial Control
- Gates / Barriers
- Remote Traffic Lights
- General Purpose Remote Control

Description

The BOGEYBOX can convert any switch into a Radio transmitter. BOGEYBOX is a self contained, four channel RF transmitter. Simply connect up to 4 x no-volt switches to the screw terminals to operate. Supplied in an IP68 Wall mounting enclosure.

Ordering Information:

Part Number	Description
BOGEYBOX-8T4	4 channel 868MHz transmitter +22dBm
BOGEYBOX-9T4	4 channel 918MHz transmitter +22dBm

BOGEYBOX RF Transmitter



Operation

BOGEYBOX will remain in a "Deep Sleep" mode at all times when no inputs are active. When any of the No-Volt inputs change state, (Closes or Opens) BOGEYBOX will wake up and Transmit an RF signal. The LED Flashes to indicates RF Transmission.

Pairing to a Receiver

BOGEYBOX, can be used with any RF Solutions Receiver operating at the same frequency.

Technical Specifications:

Operating temperature: 0 - 60°C, Storage Temperature: -10 - 85°C

Supplied Battery AAA LR03 1.5V X2

Electrical Characteristics	Min	Typical	Max	Units
Supply Voltage Battery External Supply	2.8 5	3.00	15	V
Operating Frequency		869.500 918.000		MHz
RF Transmit power ERP			+22	dBm
Time from I/P Active to Receiver O/P Active FM LoRa Mode7 (worst Case)		25 1280		mSecs
Supply Current Asleep (between readings) Battery External Supply		1 70		uA
Supply Current Whilst Transmitting		118		mA
RF Packet TX Transmit operation: FM Mode LoRa Mode 7		20 1.28		mSecs Secs

Battery Life (Estimated)

Depends on several factors;

- The time interval between RF Transmissions
- FM / FHSS LoRa Mode 1-7

Operations	FSK	FHSS (LoRa)7
1 per Min	8 months	1 month
2 per Hour	19 years	4 months
1 per Hour	39 years	1 year

RF Solutions Ltd. Recycling Notice

Meets the following EC Directives:

DO NOT Discard with normal waste, please recycle.

ROHS Directive 2011/65/EU and amendment 2015/863/EU

Specifies certain limits for hazardous substances.

WEEE Directive 2012/19/EU Waste electrical & electronic equipment. This product must be disposed of through a licensed WEEE collection point.

RF Solutions Ltd., fulfils its WEEE obligations by membership of an approved compliance scheme, environment agency registration number **WEE/JB0104WV**.



Waste Batteries and Accumulators Directive 2006/66/EC

Where batteries are fitted, before recycling the product, the batteries must be removed and disposed of at a licensed collection point.

RF Solutions battery producer number:
BPRN00060.

Disclaimer:

Whilst the information in this document is believed to be correct at the time of issue, RF Solutions Ltd does not accept any liability whatsoever for its accuracy, adequacy or completeness. No express or implied warranty or representation is given relating to the information contained in this document. RF Solutions Ltd reserves the right to make changes and improvements to the product(s) described herein without notice. Buyers and other users should determine for themselves the suitability of any such information or products for their own particular requirements or specification(s). RF Solutions Ltd shall not be liable for any loss or damage caused as a result of user's own determination of how to deploy or use RF Solutions Ltd's products. Use of RF Solutions Ltd products or components in life support and/or safety applications is not authorised except with express written approval. No licences are created, implicitly or otherwise, under any of RF Solutions Ltd's intellectual property rights. Liability for loss or damage resulting or caused by reliance on the information contained herein or from the use of the product (including liability resulting from negligence or where RF Solutions Ltd was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict RF Solutions Ltd's liability for death or personal injury resulting from its negligence.