PH20100S



N-channel TrenchMOS standard level FET

Rev. 03 — 2 February 2009

Product data sheet

1. Product profile

1.1 General description

Standard level N-channel enhancement mode Field-Effect Transistor (FET) in a plastic package using TrenchMOS technology. This product is designed and qualified for use in computing, communications, consumer and industrial applications only.

1.2 Features and benefits

- Higher operating power due to low thermal resistance
- Low conduction losses due to low on-state resistance
- Simple gate drive required due to low gate charge current

1.3 Applications

■ DC-to-DC convertors

Switched-mode power supplies

1.4 Quick reference data

Table 1. Quick reference

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
V_{DS}	drain-source voltage	$T_j \ge 25 \text{ °C}; T_j \le 150 \text{ °C}$	-	-	100	V
I_D	drain current	$T_{mb} = 25 ^{\circ}\text{C}; V_{GS} = 10 \text{V};$ see <u>Figure 2</u> ; see <u>Figure 1</u>	-	-	34.3	Α
P _{tot}	total power dissipation	$T_{mb} = 25 ^{\circ}C$	-	-	62.5	W
Dynamic	characteristics					
Q_{GD}	gate-drain charge	$V_{GS} = 10 \text{ V}; I_D = 20 \text{ A};$ $V_{DS} = 50 \text{ V}; T_j = 25 \text{ °C};$ see Figure 11	-	8.9	-	nC
Static ch	aracteristics					
R _{DSon}	drain-source on-state resistance	$V_{GS} = 10 \text{ V}; I_D = 10 \text{ A};$ $T_j = 25 \text{ °C}; \text{ see } \frac{\text{Figure 8}}{\text{see } \frac{\text{Figure 9}}{\text{otherwise}}};$	-	19	23	mΩ



N-channel TrenchMOS standard level FET

2. Pinning information

Table 2. Pinning information

Pin	Symbol	Description	Simplified outline	Graphic symbol
1	S	source		_
2	S	source	mb	D
3	S	source		$G \left(\stackrel{\longleftarrow}{\bowtie} \stackrel{\longleftarrow}{A} \right)$
4	G	gate	Qj	<u> </u>
mb	D	mounting base; connected to drain	1 2 3 4	mbb076 S
			SOT669 (LFPAK)	

3. Ordering information

Table 3. Ordering information

Type number	Package		
	Name	Description	Version
PH20100S	LFPAK	plastic single-ended surface-mounted package (LFPAK); 4 leads	SOT669


4. Limiting values

Table 4. Limiting values

In accordance with the Absolute Maximum Rating System (IEC 60134).


Symbol	Parameter	Conditions	Min	Max	Unit
V_{DS}	drain-source voltage	T _j ≥ 25 °C; T _j ≤ 150 °C	-	100	V
V_{GS}	gate-source voltage		-20	20	V
I_D	drain current	$V_{GS} = 10 \text{ V}; T_{mb} = 100 \text{ °C}; \text{ see } \frac{\text{Figure 2}}{\text{Model}}$	-	21.6	Α
		V _{GS} = 10 V; T _{mb} = 25 °C; see <u>Figure 2</u> ; see <u>Figure 1</u>	-	34.3	Α
I _{DM}	peak drain current	$t_p \le 10 \ \mu s$; pulsed; $T_{mb} = 25 \ ^{\circ}C$; see Figure 1	-	137	Α
P _{tot}	total power dissipation	$T_{mb} = 25 ^{\circ}C$	-	62.5	W
T _{stg}	storage temperature		-55	150	°C
Tj	junction temperature		-55	150	°C
Source-dr	ain diode				
Is	source current	$T_{mb} = 25 ^{\circ}C$	-	52	Α
I _{SM}	peak source current	$t_p \le 10 \ \mu s$; pulsed; $T_{mb} = 25 \ ^{\circ}C$	-	137	Α
Avalanche	ruggedness				
E _{DS(AL)S}	non-repetitive drain-source avalanche energy	V_{GS} = 10 V; $T_{j(init)}$ = 25 °C; I_D = 12 A; $V_{sup} \le$ 100 V; unclamped; t_p = 0.3 ms	-	250	mJ

N-channel TrenchMOS standard level FET



 $T_{mb} = 25$ °C; I_{DM} is single pulse; $V_{GS} = 10V$

Fig 1. Safe operating area; continuous and peak drain currents as a function of drain-source voltage



 $I_{der} = \frac{I_D}{I_{D(25^{\circ}C)}} \times 100 \%$

Fig 2. Normalized continuous drain current as a function of mounting base temperature

N-channel TrenchMOS standard level FET

5. Thermal characteristics

Table 5. Thermal characteristics

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
$R_{th(j-mb)}$	thermal resistance from junction to mounting base	see Figure 3	-	-	2	K/W




Fig 3. Transient thermal impedance from junction to mounting base as a function of pulse duration


N-channel TrenchMOS standard level FET

6. Characteristics


Table 6. Characteristics

Table 6.	Characteristics					
Symbol	Parameter	Conditions	Min	Тур	Max	Unit
Static cha	aracteristics					
$V_{(BR)DSS}$	drain-source breakdown voltage	$I_D = 1 \text{ mA}; V_{GS} = 0 \text{ V}; T_j = 25 \text{ °C}$	100	-	-	V
$V_{GS(th)}$	gate-source threshold voltage	$I_D = 1 \text{ mA}$; $V_{DS} = V_{GS}$; $T_j = 25 \text{ °C}$; see Figure 7	2	3	4	V
		$I_D = 1$ mA; $V_{DS} = V_{GS}$; $T_j = 150$ °C; see Figure 7	1.2	-	-	V
I _{DSS}	drain leakage current	$V_{DS} = 100 \text{ V}; V_{GS} = 0 \text{ V}; T_j = 25 ^{\circ}\text{C}$	-	0.06	1	μΑ
		$V_{DS} = 100 \text{ V}; V_{GS} = 0 \text{ V}; T_j = 150 \text{ °C}$	-	-	500	μΑ
I_{GSS}	gate leakage current	$V_{GS} = 20 \text{ V}; V_{DS} = 0 \text{ V}; T_j = 25 \text{ °C}$	-	2	100	nA
		$V_{GS} = -20 \text{ V}; V_{DS} = 0 \text{ V}; T_j = 25 \text{ °C}$	-	2	100	nA
R _{DSon}	drain-source on-state resistance	$V_{GS} = 10 \text{ V}; I_D = 10 \text{ A}; T_j = 150 ^{\circ}\text{C};$ see <u>Figure 8</u> ; see <u>Figure 9</u>	-	43	53	mΩ
		V_{GS} = 10 V; I_D = 10 A; T_j = 25 °C; see <u>Figure 8</u> ; see <u>Figure 9</u>	-	19	23	mΩ
Dynamic	characteristics					
Q _{G(tot)}	total gate charge	$I_D = 20 \text{ A}; V_{DS} = 50 \text{ V}; V_{GS} = 10 \text{ V};$	-	39	-	nC
Q_{GS}	gate-source charge	T _j = 25 °C; see <u>Figure 11</u>	-	6.9	-	nC
Q_{GD}	gate-drain charge		-	8.9	-	nC
C _{iss}	input capacitance	$V_{DS} = 25 \text{ V}; V_{GS} = 0 \text{ V}; f = 1 \text{ MHz};$	-	2264	-	рF
C _{oss}	output capacitance	T _j = 25 °C; see <u>Figure 12</u>	-	290	-	pF
C _{rss}	reverse transfer capacitance		-	111	-	pF
t _{d(on)}	turn-on delay time	$V_{DS} = 50 \text{ V}; R_L = 5 \Omega; V_{GS} = 10 \text{ V};$	-	23	-	ns
t _r	rise time	$R_{G(ext)} = 4.7 \Omega$; $I_D = 10 A$; $T_j = 25 °C$	-	15	-	ns
t _{d(off)}	turn-off delay time		-	47	-	ns
t _f	fall time		-	9.3	-	ns
Source-d	rain diode					
V_{SD}	source-drain voltage	$I_S = 10 \text{ A}; V_{GS} = 0 \text{ V}; T_j = 25 ^{\circ}\text{C};$ see <u>Figure 10</u>	-	0.8	1.2	V
t _{rr}	reverse recovery time	$I_S = 20 \text{ A}$; $dI_S/dt = -100 \text{ A/}\mu\text{s}$; $V_{GS} = 0 \text{ V}$; $V_{DS} = 25 \text{ V}$; $T_i = 25 \text{ °C}$	-	110	-	ns

N-channel TrenchMOS standard level FET



Output characteristics: drain current as a function of drain-source voltage; typical values



$$T_j = 25$$
°C and 150 °C; $V_{DS} > I_D \times R_{DSon}$

Fig 5. Transfer characteristics: drain current as a function of gate-source voltage; typical values




Fig 6. Sub-threshold drain current as a function of

gate-source voltage




Fig 7. Gate-source threshold voltage as a function of junction temperature

Fig 4.

N-channel TrenchMOS standard level FET






Fig 8. Drain-source on-state resistance as a function of drain current; typical values




$$a = \frac{R_{DSon}}{R_{DSon(25^{\circ}C)}}$$

Fig 9. Normalized drain-source on-state resistance factor as a function of junction temperature



 $T_{j}=25^{\circ}C \, {\rm and} \, 150^{\circ}C; V_{GS}=0V$ Fig 10. Source current as a function of source-drain


voltage; typical values



 $I_D = 20A; V_{DS} = 50V$

Fig 11. Gate-source voltage as a function of gate charge; typical values

N-channel TrenchMOS standard level FET




 $V_{GS} = 0V; f = 1MHz$

Fig 12. Input, output and reverse transfer capacitances as a function of drain-source voltage; typical values

Package outline

Plastic single-ended surface-mounted package (LFPAK); 4 leads

SOT669



	UNIT	Α	A ₁	A ₂	A ₃	b	b ₂	b ₃	b ₄	С	c ₂	D ⁽¹⁾	D ₁ ⁽¹⁾ max	E ⁽¹⁾	E ₁ ⁽¹⁾	е	Н	L	L ₁	L ₂	w	у	θ
	mm	1.20 1.01	0.15 0.00	1.10 0.95	0.25	0.50 0.35	4.41 3.62	2.2 2.0	0.9 0.7	0.25 0.19		4.10 3.80	4.20	5.0 4.8	3.3 3.1	1.27	6.2 5.8	0.85 0.40	1.3 0.8	1.3 0.8	0.25	0.1	8° 0°
L									-					_	-								-

Note

^{1.} Plastic or metal protrusions of 0.15 mm maximum per side are not included.

OUTLINE		REFER	ENCES	EUROPEAN	ISSUE DATE
VERSION	IEC	JEDEC	JEITA	PROJECTION	ISSUE DATE
SOT669		MO-235			04-10-13 06-03-16

Fig 13. Package outline SOT669 (LFPAK)

N-channel TrenchMOS standard level FET

8. Revision history

Table 7. Revision history

Document ID	Release date	Data sheet status	Change notice	Supersedes
PH20100S_3	20090202	Product data sheet	-	PH20100S_2
Modifications:	guidelines	of this data sheet has been of NXP Semiconductors. have been adapted to the		•
PH20100S_2 (9397 750 13698)	20040817	Product data sheet	-	PH20100S_1
PH20100S_1 (9397 750 12815)	20040305	Preliminary data sheet	-	-

N-channel TrenchMOS standard level FET

9. Legal information

9.1 Data sheet status

Document status [1][2]	Product status[3]	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

- [1] Please consult the most recently issued document before initiating or completing a design.
- [2] The term 'short data sheet' is explained in section "Definitions"
- [3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL http://www.nexperia.com.

9.2 Definitions

Draft — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. Nexperia does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local Nexperia sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

9.3 Disclaimers

General — Information in this document is believed to be accurate and reliable. However, Nexperia does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information.

Right to make changes — Nexperia reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — Nexperia products are not designed, authorized or warranted to be suitable for use in medical, military, aircraft, space or life support equipment, nor in applications where failure or malfunction of a Nexperia product can reasonably be expected to result in personal injury, death or severe property or environmental damage. Nexperia accepts no liability for inclusion and/or use of Nexperia products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. Nexperia makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Quick reference data — The Quick reference data is an extract of the product data given in the Limiting values and Characteristics sections of this document, and as such is not complete, exhaustive or legally binding.

Limiting values — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) may cause permanent damage to the device. Limiting values are stress ratings only and operation of the device at these or any other conditions above those given in the Characteristics sections of this document is not implied. Exposure to limiting values for extended periods may affect device reliability.

Terms and conditions of sale — Nexperia products are sold subject to the general terms and conditions of commercial sale, as published at http://www.nexperia.com/profile/terms, including those pertaining to warranty, intellectual property rights infringement and limitation of liability, unless explicitly otherwise agreed to in writing by Nexperia. In case of any inconsistency or conflict between information in this document and such terms and conditions, the latter will prevail.

No offer to sell or license — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

9.4 Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

10. Contact information

For more information, please visit: http://www.nexperia.com

For sales office addresses, please send an email to: salesaddresses@nexperia.com

PH20100S

N-channel TrenchMOS standard level FET

11. Contents

Nexperia

1	Product profile
1.1	General description
1.2	Features and benefits1
1.3	Applications1
1.4	Quick reference data1
2	Pinning information2
3	Ordering information2
4	Limiting values2
5	Thermal characteristics4
6	Characteristics5
7	Package outline9
8	Revision history10
9	Legal information11
9.1	Data sheet status
9.2	Definitions
9.3	Disclaimers
9.4	Trademarks11
40	Cantact information 44