

4-in-1 Battery Charger

MODEL NUMBER: UBC41







Versatile dual-input voltage battery charger compatible with any lead acid battery, including gel-type, maintenance-free, AGM and Ni-MH. Ideal for workbenches, construction sites, warehouses and other workspaces.

Description

The versatile UBC41 4-in-1 Battery Charger has many uses from charging the dead battery in your automobile or golf cart to various fleet and industrial operations. Compatible with any lead acid battery, including gel-type, maintenance-free, absorbent glass mat (AGM) and Ni-MH, the UBC41 operates on either 120V or 240V AC input mains voltage at an automatically selected 50 Hz or 60 Hz. The charger works with 12-, 24-, 36- or 48-volt batteries at high or low charge rates. Use the included alligator clips to connect the charger to the battery.

LED display monitors charge rate, battery capacity and float status. It also informs you of charging errors, such as a blown fuse, at a glance. Built-in cooling fan and automatic shutdown feature protect the unit from overheating. The charger is also protected from short circuits and accidental reverse connections.

The rugged aluminum housing is designed to handle day-to-day stress. Built-in mounting feet allow the UBC41 to be permanently installed on any rigid horizontal surface with user-supplied hardware.

Features

Digital Power Electronics for Accurate, Reliable Operation

- All-in-one charger compatible with 12V, 24V, 36V and 48V batteries
- Selectable high and low charge rates (H/L 12V/24V: 30A/10A; 36V: 25A/10A; 48V: 15A/7A)
- Selectable 120V or 240V input mains voltage
- Automatically selects 50 Hz or 60 Hz

Charges Lead Acid Batteries

· Including gel-type, maintenance-free, AGM and Ni-MH

Highlights

- Charges 12V, 24V, 36V and 48V batteries
- Selectable 120V or 240V input mains voltage (50/60 Hz)
- Compatible with lead acid batteries
- Easy-to-read LED display monitors charge status
- Keeps battery at full capacity without overcharging

Package Includes

- UBC41 4-in-1 Battery Charger
- Alligator clips with cable
- Power cord with NEMA 5-15P plug
- Owner's manual



• Comes with alligator clips for connection

Easy-to-Read LED Display

- Yellow and green LEDs monitor charge rate, battery capacity and float status
- Red LED alerts you to overheating, wrong battery voltage and other charging errors

Protection Functions

- Shuts down automatically upon overheating, and restarts when cooled to appropriate temperature
- Won't operate when battery connectors are attached in reverse

Durable Construction

- Rugged aluminum housing stands up to daily use
- Built-in mounting feet allow installation on any rigid horizontal surface

Specifications

OVERVIEW		
UPC Code	037332191533	
Accessory Type	Battery Charger	
Accessory Class	Power Inverter Accessories	
INPUT		
Nominal Input Voltage(s) Supported	120V AC; 240V AC	
Input Connection Type	NEMA 5-15P power cord	
OUTPUT		
Frequency Compatibility	50 / 60 Hz	
BATTERY		
Battery Charge	Selectable high and low charge rates (H/L 12V/24V: 30A/10A; 36V: 25A/10A; 48V: 15A/7A)	
USER INTERFACE, ALERTS & CONTROLS		
Diagnostic LED(s)	Yes	
Diagnostic LED Details	Yellow and green LEDs monitor charge rate, battery capacity and float status. Red LED alerts you to overheating, wrong battery voltage and other charging errors.	
PHYSICAL		
Material of Construction	Aluminum	
Color	Silver	
Shipping Dimensions (hwd / cm)	17.58 x 25.68 x 37.59	



Shipping Dimensions (hwd / in.)	6.92 x 10.11 x 14.80
Shipping Weight (kg)	5.13
Shipping Weight (lbs.)	11.30
Unit Dimensions (hwd / in.)	3.96 x 8.78 x 11.81
Unit Dimensions (hwd / cm)	10.06 x 22.30 x 29.99
Unit Weight (Ibs.)	9.7
Unit Weight (kg)	4.40
WARRANTY	
Product Warranty Period (Worldwide)	1-year limited warranty

© 2022 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies